

# High Power Handheld Signal Jammer HS-P8J

(For worldwide all Networks)



## Application

Police, Bomb disposal squads, VIP protection, Special Police (S.W.A.T), military security forces, bomb squads, anti-terror units, anti-drug units, Border control units, checkpoint personnel, Meeting room, Hospitals, Banks, Church, Conference Rooms, Classrooms and so on, such types of law enforcement personnel who benefit greatly from the deployment of any state in the art portable RF jamming solutions, who can conduct the law enforcement process more effectively to reduce the chance that the criminals leak the information.

## Accessories

Nylon Cover, Antenna, AC Power Adapter. DC12V Car Charger



## Features and Advantages Of HS-P8J

- Inside cooling fans and big heat sink design ensure the device to work continuously.
- With internal rechargeable battery. Simple to be replaced.
- With a display to show the battery status.
- With longer 2.5dbi gains omni antennas,
- High-power Multi-band Handheld jammer.
- It can keep working while charging.
- It can last around 2.5 hours after fully charged.
- Configured to block 8 different frequency bands continuously or simultaneously. Separate switch for each band with a working LED.
- Could be used in car directly, with car charger and AC charger
- Total RF output power is up to 5.6 watt. Asia Market



## Technical Specification

Model Number: HS-P8J			
Type	Output Port	Frequency	Radius Range
Asia Market customized as required.	CDMA800	869-894MHz	5-10M @ depending on the mobile service provider's network condition
	GSM90	935-960MHz	
	DCS1800	1805-1880Mhz	
	WCDMA	2110-2170MHz	
	LTE4G,2300	2300-2400MHz	
	LTE4G,1800	1805-1880Mhz	
	WIFI/Bluetooth or WIFI5.8G or WIFI5.2G	2400-2500MHz or 5725-5850MHz or 5125-5350MHz	
	GPSL1	1575.42MHz	
Net weight with antennas: 0.8Kg			
Jammer Size: 156*83*48mm (not include antenna)			
Total Power Consumption: Approx.30watt			
Power supply: AC110-240V/ 12VDC Built-in Battery: 8000mAh			

**Cautions**

- Be sure to connect all the antennae before the power supply is switch on.
- Try to recharge the device only once battery is run-out when you get the device in the first time.
- With the increase of charging electricity, charging indication light from Red to Green is fully charged.
- Don't put the jammer into the water or fire to avoid using in the bad Condition like over-wet, over-hot, high voltage and high magnetism.
- Any sealed mark on the machine tore is invalid.
- Antennae shall be put vertical to the ground to get more efficient jamming performance.